



The CX-MAG2588 series of remote paging selectors have the same high stability as traditional ones, and they operate reliably with a low failure rate. It uses an all-digital signal transmission system, with intelligent control at its core. The 7-inch LCD true colour LCD panel with touch screen control, graphics, and text interfaces is more user-friendly. It can expand local audio and amplifiers by using auxiliary input and output channels.

SPECIFICATIONS

Input sensitivity	Mic: 10mV(±1mV), unbalance Line: 300mV(±50mV), unbalance
Audio signal output	Line output: 1V (±0.1V)
	Chime output: 0.8V-1V
Chime output type	CHIME1: note1-3-5-i
	CHIME2: notei-5-3-1
	CHIME3: note i-5-i-5
Frequency response	Mic: 150Hz-10kHz(±3dB); Line: 20Hz-20kHz(±3dB)

Distortion	MIC: ≤1.5%
	Line: ≤0.1%
Signal to noise ratio	Mic input ≥60dB Line input ≥70dB
Protection	AC fuseF1L
Power	AC 220-240V/50-60Hz/5W
Device size(mm)	(L×W×H)270×180×120
Gross weight	3.5kg
Net weight	2.2kg