



CX-MAG505 audio router is designed to support 5 audio outputs, with the ability of selecting one of four audio sources for each output independently. It's a stereo gadget with an RS232 interface and wall-mounted touchpads for controlling the primary functions. The MAG505 features an integrated USB player as well as Bluetooth and FM receivers. Priority input for emergency audio; external mute contact in an emergency.

SPECIFICATIONS

Model	CX-MAG505
Power Supply	100-240VAC, 50/60Hz
Fuse	T1AL
Media Player	USB/Bluetooth
Bluetooth Version	V5.0
MIC Input Sensitivity	-41dBV
Line Input Sensitivity	-12.5dBV
Call Station Input Sensitivity	+4dBV
EMC Input	Sensitivity -10dBV

SN Ratio to MIC Input	65dB
SN Ratio to Line Input	73dB
Outputs	5 stereo zones
Output Impedance	600 ohm
THD+N	< 0.1%@1KHz
Phantom Power	+24V DC
Frequency Response	±3dB 20Hz-20kHz
Dimensions	483×177×44mm
Weight	1.76kg