



- Condenser microphone.
- Cardioid polar pattern.
- With signal indicator for working status.
- Five zones selection and all zone selection.
- With 1 Aux input.
- Aux input/Mic/Chime with individual adjustment.
- 1 RJ45 for connection with the host.
- Power supply: DC24V.

CX-MAG505R paging microphone has a condenser microphone. With signal indicators, it can display the working status of each zone. It has RJ45 port and 3.5mm stereo RCA port, as well as RS485 port.

## SPECIFICATIONS

<b>Model</b>	CX-MAG505R
<b>Power Supply</b>	24VDC, 500mA
<b>MAX. Connection Length</b>	500m
<b>Microphone Type</b>	Condenser microphone
<b>Polar Pattern</b>	Cardioid
<b>Connectors</b>	RJ45, 24VDC power jack, 3.5mm stereo RCA
<b>Frequency Response</b>	-3dB 150Hz-22kHz

<b>Input Level MIC</b>	-46dBV, Aux: -10dBV
<b>Output Impedance</b>	Balanced 600 Ohms
<b>Input Impedance MIC</b>	600 Ohms, AUX: 50k Ohms
<b>Output Level</b>	10dBV
<b>S/N Ratio</b>	-60dB
<b>Interface</b>	RS-485
<b>Dimensions</b>	460mm×140mm×115mm
<b>Weight</b>	670g