



The CX-DMA6250U Digital Mixer Amplifier can be used in conjunction with the CX-DMA20 Remote Paging Station to handle a 2-channel RJ-45 remote paging microphone. The amplifier features an intuitive display panel with input sources including 4 MIC, 4 AUX, USB, FM, Bluetooth, and TF. It also provides protection against overload, clipping, short circuits, and excessive working temperatures. It is a multifunctional amplifier designed to fulfil the needs of its consumers.

SPECIFICATIONS

Model	CX-DMA6250U
Power	AC220-230V 50/60Hz
MIC1	5mV ±1mv (Balanced XLR Input)
MIC2/MIC3/MIC4	5mV ±1mv (Unbalanced Phoenix Jacks)
AUX1	350mV±50mv (Unbalanced RCA Input)
AUX2/EMC	350mV ±50mv (Unbalanced Phoenix Jacks)
MIC Frequency Response	120Hz ~ 12kHz (±3dB)
AUX Frequency Response	80Hz ~ 15kHz (±3dB)
THD	<1%
Treble Adjustment Range	10dB (±2)

BASS Adjustment Range	10dB (±2)
Phantom Power	+48V
Rated Output Power	250W
Output Voltage of Port	4-16Ω, 70V, 100V (fixed voltage output)
Current	2A
Protection	F3.15AL
Machine Dimension (D×W×H)	430×390×88mm
Package Dimension	545×500×165mm
Net Weight	8.6KG
Gross Weight	9.8KG