



ConnexAV

# CX-MAG808C

8x8 Audio Matrix Switcher



The CX-MAG808C is a remote control panel that supports DC24V and includes a digital screen. It can operate eight different zones. One microphone input (MIC) and one line input, each with their own volume control knob, are both included on this panel.

## SPECIFICATIONS

<b>Model</b>	CX-MAG808C
<b>Power</b>	DC 24V
<b>MICinput sensitivity</b>	10±2mV
<b>LINEinput sensitivity</b>	300±50mV
<b>USBinput sensitivity</b>	-10dB
<b>MIC frequency response</b>	100Hz ~ 15kHz ( ±3dB )
<b>AUX frequency response</b>	20Hz ~ 20kHz ( ±3dB )
<b>Noise</b>	<0.5mV

<b>Distortion</b>	<0.5% 1KHz
<b>Rated power</b>	DC 24V
<b>Net port output level(balance )</b>	2000±100mV
<b>Machine size(LxWxH)</b>	145mmx80mmx47mm
<b>Packing size(LxWxH)</b>	310mmx180mmx95mm (1PS)
<b>Net weight</b>	0.4Kg
<b>Gross weight</b>	0.7Kg (1PS)